




## **ELECTRIC CONTROL PANELS**

## FFBJP RANGE (FFB UNITS JOCKEY PUMP)



Control panels for fire-fighting units in compliance with EN 12845 for compensation electric pumps.

Every control panel is set-up to control an electric pump.

- The start consent is given by the minimum pressure in the system and by the minimum water level in the suction tank. Any intervention of the level indicator due to lack of water, stops the electric pump.
- Motor overloading is controlled by the circuit breaker relay and indicated on the control panel.

## **TECHNICAL DATA**

- Power supply: 400V ±10- 50/60 Hz
- Temperature limits: -10°C ÷ + 40°C
- IP55 Protection rating
- Reference Standards: EN 60204-1; EN 60439-1; EN 61000-6-1; EN 61000-6-2; EN 61000-6-3; EN 61000-6-4; EN 60529; EN 12845